



Electrical Connection 7/8"

Small Line - Air Cooled Condenser Electrical Data

Model	Fan Motor		1075 RPM Condenser Electrical Data - 60 Hz								
	HP	Qty.	208-230/1/60 (208-230/3/60)*			460/1/60 (460/3/60)*			575/1/60 (575/3/60)*		
			FLA	MCA	MOP	FLA	MCA	MOP	FLA	MCA	MOP
KS11-031	1/6	1	1.1	1.4	15	0.6	0.8	15	0.5	0.7	15
KS11-039	1/6	1	1.1	1.4	15	0.6	0.8	15	0.5	0.7	15
KS11-065	1/3	1	2.1	2.7	15	1.1	1.4	15	0.9	1.2	15
KS11-078	1/3	1	2.1	2.7	15	1.1	1.4	15	0.9	1.2	15
KS11-097	1/3	1	2.1	2.7	15	1.1	1.4	15	0.9	1.2	15
KS12-128	1/3	2	4.2	4.8	15	2.2	2.5	15	1.8	2.1	15
KS12-154	1/3	2	4.2	4.8	15	2.2	2.5	15	1.8	2.1	15
KS12-176	1/3	2	4.2	4.8	15	2.2	2.5	15	1.8	2.1	15
KS12-193	1/3	2	4.2	4.8	15	2.2	2.5	15	1.8	2.1	15
KS13-230	1/3	3	6.3 (3.6)	6.9 (4.6)	15	3.3 (1.9)	3.6 (2.4)	15	2.7 (1.6)	3.0 (2.0)	15
KS13-288	1/3	3	6.3 (3.6)	6.9 (4.6)	15	3.3 (1.9)	3.6 (2.4)	15	2.7 (1.6)	3.0 (2.0)	15

FLA = Full Load Amps MCA = Maximum Current Ampacity MOP = Maximum Overcurrent Protection

* 3 Phase Power Connection Available on 3 Fan Models Only

In the interest of continuous improvement, ClimateWorx reserves the right to change specifications without notice - May 2009. While every endeavor is made to ensure accuracy, ClimateWorx International Inc. accepts no responsibility or liability resulting from the use of this information