



**Electrical Connection 7/8"**

**Small Line - Air Cooled Condenser Electrical Data**

Model	Fan Motor		1075 RPM Condenser Electrical Data - 60 Hz								
	HP	Qty.	208-230/1/60 (208-230/3/60)*			460/1/60 (460/3/60)*			575/1/60 (575/3/60)*		
			FLA	MCA	MOP	FLA	MCA	MOP	FLA	MCA	MOP
KS11-031	1/3	1	1.7	2.1	15	0.9	1.1	15	0.7	0.9	15
KS11-039	1/3	1									
KS11-065	1/3	1	3.0	3.8	15	1.4	1.8	15	1.2	1.5	15
KS11-078	1/3	1									
KS11-097	1/3	1									
KS12-128	1/3	2	5.1	5.9	15	2.5	2.9	15	2.1	2.4	15
KS12-154	1/3	2									
KS12-176	1/3	2									
KS12-193	1/3	2									
KS13-230	1/3	3	7.2 (4.1)	8.0 (4.6)	15	3.6 (2.1)	4.0 (2.3)	15	3.0 (1.7)	3.3 (1.9)	15
KS13-288	1/3	3									

FLA = Full Load Amps      MCA = Maximum Current Ampacity      MOP = Maximum Overcurrent Protection

\* 3 Phase Power Connection Available on 3 Fan Models Only

In the interest of continuous improvement, ClimateWorx reserves the right to change specifications without notice - July 2015

While every endeavor is made to ensure accuracy, ClimateWorx International Inc. accepts no responsibility or liability resulting from the use of this information.